

LINEARlight ADVANCED Overall Module

硬灯条模组适用于专业照明领域



产品特点

- 面向设计的成套模块，带 14 个 LED 和集成式光学组件
- 光通量与T5日光灯管（8 W、13 W）的光通量相当
- 光通量：高达1,250 lm/m
- 颜色渲染指数 R_a ：85，典型值
- 可调光
- 一个电子镇流器可连接多达 10 个模块
- 与LINEARlight POWER和ECO Overall Module兼容

产品优势

- 平型结构的高度：13 mm
- 通过铝外壳充分散热
- 模组可方便连接在一起，以制作无缝灯带
- 使用寿命长达 50,000 小时（L70/B50），维护成本低

应用领域

- 暗槽照明
- 储柜和碗柜照明

产品系列数据表

设备/配件

- CONNECTsystem LR
- 安装支架LD-MB
- LT-ENDCAP-G2

应用建议

更多详细应用信息和图形,请参阅产品数据表。

数据表文本

- Installation of LED modules (with power supplies) needs to be made under consideration of all valid regulations and norms.
- Installation by qualified electrician only.
- Please see the relevant application guides and instructions sheets for more detailed safety and mounting information. Additional information is available on request.
- Complies with IEC/EN 61547
- Complies with IEC/EN 61000-3-2
- Complies with EN 55015, CISPR 15
- Complies with IEC/EN 61347-1
- Complies with IEC/EN 61347-2-13
- Suitable for usage in furnitures (DIN 57710).
- LED modules are dimmable by means of PWM (pulse width modulation). It is recommended using the following OSRAM control gears: OPTOTRONIC OT DIM, OT DALI DIM or OPTOTRONIC 24 V power supplies with integrated 1...10 V dimming interface.
- Parallel connection is mandatory for safe electrical operation. Serial connection of LED modules is strongly discouraged. Unbalanced voltage drop in serial connection can cause hazardous overload and damage the LED module.
- Electrical contact is achieved with the contact cables or the terminals of the module. Please refer to the technical data for maximum number of LED modules that can be operated on one control gear.
- In order to operate OSRAM LED modules safely, it is absolutely necessary to operate them with an electronically stabilized power supply that protects against short circuits, overload and overheating.
- In case other power supplies than OSRAM OPTOTRONIC are used, compliance to the necessary operating parameters (voltage, current, power) has to be ensured.
- Pay attention to polarity! Wrong polarity can cause destruction or malfunction of the module.
- Use only coordinated LR-4PIN CONNECTsystem for electrical installation.
- Conducting paths on the circuit board must not be damaged or destroyed during installation.
- Luminaire must be cleaned regularly to avoid loss of luminous flux.
- The LED module itself and all its components must not be stressed mechanically.
- Operation in or under water is prohibited.
- Protect against splashes!
- The module, as manufactured, has no inherent protection against corrosion. It is the user's responsibility to provide suitable protection against corrosive agents, such as moisture, condensation and other harmful elements.
- To avoid mechanical damage, the LED modules have to be attached securely to the intended mounting surface. It is recommended to avoid heavy vibration.

销售和技术支持

销售和技术支持 www.osram.cn

Ecodesign regulation information:

- This product is considered to be a "containing product" in the sense of Regulations (EU) 2019/2020 and (EU) 2019/2015.
- Tolerances of the reported values, are according to LED Modules Performance standard IEC/EN 62717.
- In general, the replacement of the contained light sources without permanent damage to the product with the use of common available tools is possible in the final application when they can be dismantled from the installation environment and substituted for the necessary number of light sources restoring its full electrical/mechanical/thermal/optical functionality by means of a professional installer. In the contrary, and limited to the LINEARlight Flex Diffuse, LINEARlight Rigid Finesse, GINO LED Flex Diffuse and LUMINENT Milky product families, the contained light source is an integrated part of the containing product and its removal can only be done by causing a permanent damage to the containing product due to its tight mechanical, electrical, optical, thermal interaction and/or environmental protection with or from the containing product. Therefore, a replacement of the light source with the use of common available tools is not justified.
- Dismantling of light sources from containing products at end of life: Containing products with light sources which are scalable in length can be cut to the length of the contained light source and if applicable mechanically detached from protective and/or optical covers. Containing products shall be separated from building material and/or from other additional mounting accessories by means of a professional installer. Separate control gear and light sources must be disposed of at certified disposal companies in accordance with Directive 2012/19/EU (WEEE) in the EU and with Waste Electrical and Electronic Equipment (WEEE) Regulations 2013 in the UK. For this purpose, collection points for recycling centres and take-back systems (CRSO) are available from retailers or private disposal companies, which accept separate control gear and light sources free of charge. In this way, raw materials are conserved and materials are recycled.

免责声明

更改恕不另行通知。遗漏错误不承担任何责任。总是确保使用最新的信息。