

OPTOTRONIC - 2DIM High Power IP67 AUX12

恒流 – 可调光



应用领域

- Area lighting
- Stadium lighting
- Horticulture lighting
- 街道和城区照明
- 适合I类保护的灯具

产品优势

- Easily programmable by OT Programmer-S; (AstroDIM / Constant lumen)
- 高效、高可靠
- 2DIM functionality in one device (AstroDIM, 1...10 V)
- 较高的浪涌防护等级：最高10 kV
- 宽工作温度范围 (-40°C...55°C)，具备极大的使用灵活性
- Lifetime: up to 100,000 h
- 5 years guarantee

产品特点

- Available with different wattage: 400 W, 600 W
- 电源电压：220至240 V
- AUX 12V output for sensor and wireless node
- Wide output current range
- 使用寿命：最大 100000 小时 (T_c 条件下 $T = 75^\circ\text{C}$ 时)

产品系列数据表

应用建议

更多详细应用信息和图形,请参阅产品数据表。

数据表文本

- Input voltage range: Nominal operation at 198 – 264 Vac.
- Output short circuit protection: shut down of driver occur in case of output short circuit without damage to the unit.
- Output over load/voltage protection: In case the input voltage of the load exceeds the output voltage range which is auto defined by output current setting of the driver ($V_o = P_o / I_o$), it automatically reduces the output current. Auto-reversible without mains power on/off;
- No load protection: the driver automatically adjusts the output voltage to the maximum output voltage which is auto defined by output current setting if no load is connected. Auto-reversible with the correct load connected;
- Over temperature protection: the driver is protected against temporary overheating by shutting down until the overheating eliminated; Auto-reversible when temperature back to normal;
- Disconnect the power before servicing. Terminal block is not included, installation must be performed by qualified person;
- The protective earth (GNYE/PE wire, housing) has to be connected to the heat sink of the LED module to improve the capability of the system to withstand a surge and EMI in critical luminaires.
- Not suitable to be mounted in ceiling corner
- The LED control gear cannot be abutted against or covered by normally flammable materials or used in installations where building insulation or debris is, or may be, present in normal use.
- The external flexible cable or cord of this driver cannot be replaced; if the cord is damaged, the driver shall be destroyed.
- The dimmer should fulfill at least basic insulation between control voltage and dimming circuit (for Australia and New Zealand).
- The startup time to reach the set output current is less than 2s.
- For further details please consult the application note;
- AUX 12V output for sensor and wireless node (max. 200 mA)
- For output cable > 2m EMC conformity is not guaranteed and must be ensured by OEM

销售和技术支持

销售和技术支持 www.osram.cn

Ecodesign regulation information:

Intended for use with LED modules.

The forward voltage of the LED light source shall be within the defined operating window of the control gear in all operating conditions including dimming if applicable.

Separate control gear and light sources must be disposed of at certified disposal companies in accordance with Directive 2012/19/EU (WEEE) in the EU and with Waste Electrical and Electronic Equipment (WEEE) Regulations 2013 in the UK. For this purpose, collection points for recycling centres and take-back systems (CRSO) are available from retailers or private disposal companies, which accept separate control gear and light sources free of charge. In this way, raw materials are conserved and materials are recycled.

参考资料/链接

* For more information on the multi-level guarantee and the terms and conditions of the guarantee visit <https://>

产品系列数据表

▶ www.inventronics-light.com/multilevel-guarantees

免责声明

更改恕不另行通知。遗漏错误不承担任何责任。总是确保使用最新的信息。